



# **Wireless Pulse Input Transmitter Module**



### Introduction

The T24-PA transmitter module collects and processes pulse related measurements, such as speed of rotation, proximity, flow and count, forming part of the T24 modular telemetry system. The data transmitted by the T24-PA can be received by multiple T24 receivers that include displays, handheld readers, analogue outputs, relay modules and computer interfaces.

T24 transmitters have been designed for battery operation and support an ultra low-power sleep mode whilst offering class leading wireless coverage and range. Configurable transmission rates from once per minute to 200 per second cope with a wide range of measurement and monitoring applications. A choice of enclosures enabling battery connection, field connectivity and environmental sealing up to IP67 ensure these modules provide a flexible solution to your wireless sensor requirements.

The T24-PA provides a range of excitations (3,5,12 volts). Inputs accept volt free contacts, open collector, 5 V logic and quadrature.

## **Features**

- Simple wireless configuration and calibration
- Wireless range up to 800 m (2,600 ft)
- Low power mode for long battery life
- Miniature PCB for OEM integration
- Free Visualisation software
- Configurable on-board pull up or pull down resistor
- Range of excitation voltages of 3, 5, 12 Volts
- Selectable measurements:
  - Frequency
  - Count
  - Quadrature
  - Mark (space)
  - Digital state
  - o RPM
  - Interval



# **T24 System Overview**



T24 Wireless Telemetry Sensor System is a modular wireless solution for industrial sensor applications.

High accuracy, high quality measurement is interfaced with simple yet powerful configuration and monitoring software.

Measurement Specifications	
Period input range	333 μS to 2 s
Frequency input range	0.5 to 3,000 Hz
RPM input range (1 pulse / rev)	30 to 180,000 RPM
Volt free input pull-up resistor	56 kΩ
Pulse input voltage range	1.2 V to 12 V
Accuracy as % input error at 1 Hz (max)	0.15%
Accuracy as % input error at 1 kHz (max)	0.25%
Internal resolution	0.25 μs
Reset count input	volt free
Reset count input pull-up resistor	20 to 50 kΩ
Excitation available	3,5,12 Vdc @ 25 mA
Transmission rates	From 5 ms to 1 per minute


Battery Life		
Transmitting results at 3 per second , no excitation required		
Pair AA cells constantly on	1 month	
Pair AA cells 12 sessions per day of 5 mins	2 years	
Pair DD cells constantly on	4.5 months	
Pair DD cells 12 sessions per day of 5 mins	>9 years	

Power Supply	
ACMi and OEM module	2.1 to 3.6 Vdc
ACM	5 to 18 Vdc

Radio	
Radio type	Licence exempt
	transceiver
Radio frequency	2.4 GHz
Transmit power	10 mW
Range	Up to 800 m

Environmental	
Operating temperature range	-20 to 55 °C
Storage temperature range (no batteries)	-40 to 85 °C
Maximum humidity	95% non-condensing
IP rating (ACM and ACMi)	IP67/Nema4





### T24-PAe

Wireless pulse input OEM transmitter module for external antenna

### T24-PAi

Wireless pulse input OEM transmitter module with integral antenna

### T24-ACM-PA

Wireless pulse input transmitter module in IP67 enclosure supporting two D batteries or external power supply

### T24-ACMi-PA

Wireless pulse input transmitter module in IP67 enclosure for two AA batteries

### T24-ACMm-PA

Wireless pulse input transmitter module in miniature IP50 enclosure

**Mantracourt Electronics Ltd** The Drive, Farringdon Exeter, Devon, UK EX5 2JB

Tel: +44 (0)1395 232020 Email: sales@mantracourt.com

mantracourt.com











